

# Access Control Readers

## BLE Mobile / 125 kHz / 13.56 MHz

LINEAR

HAF Reader  
Quick Start Guide

### 1.0 Introduction

A key component of a physical security electronic access control system, the Linear Access Control reader combines RFID and Bluetooth technology. In operation it is capable of reading data stored on physical and/or mobile credentials via radio frequency without physical contact, and then passing the data obtained to the physical access control system. Access control systems typically manage and record the movement of individuals through a protected area, such as a locked door.

This Quick Start Guide is intended for experienced installing technicians. It is a basic reference to ensure all connections are properly made. Models include Linear NBT125, BT125 and BT135. For additional information please reference Linear's website [www.linear-solutions.com](http://www.linear-solutions.com).

### 2.0 Mounting Provisions

Each reader may be installed either indoors or outdoors, mullion-mount or single-gang mount. *Please recycle any unused housing components. Installation and wiring of systems must be done in accordance with National Electrical Code, ANSI/NFPA 70. Use supplied #6 mounting screws, or equivalent security screws, for installation.*



MULLION  
(Slim Mount)



SINGLE-GANG  
(Wide Mount)

### 3.0 Reader Wiring

Wiegand	
Conductor	Function
Red	DC (8-14 VDC)
Black	Ground
Green	Data 0
White	Data 1
Brown	Red LED †
Orange	Not Used
Yellow	Not Used
Blue	Beeper
Violet	CSN Mode (BT135 only) ††
Drain	Shield Ground

#### NOTES:

† Single Line LED: This is the standard operating mode and does not make use of the Orange conductor. While idle, the LED on NBT125 models is Red and flashes when a card is presented.

While idle, the LED on BT125 and BT135 models is Blue and flashes when a card is presented.

On all models, the LED turns green when the Brown Conductor is pulled low by the access control panel.

†† Sector vs CSN: The standard operating mode for BT135 readers does not make use of the Purple conductor and will only output a smart card's Sector data. Pulling the Purple conductor low (grounded) will cause the reader to output a smart card's CSN data.

### 4.0 Cable Requirements

**For Cable runs of LESS THAN 300FT:** 24 AWG minimum, multi-conductor stranded with an overall foil shield, for example Belden 9535 or similar, supporting the five conductors comprising the physical layer of the Wiegand interface (power, ground, data 0, data 1, and/or beeper and LED). Alternatively, Belden 9539 equivalent or higher quality, for all reader functions.

**For Cable runs of 300-500FT:** 22 AWG minimum, multi-conductor stranded with an overall foil shield, for example Belden 8445 or similar, supporting the five conductors comprising the physical layer of the Wiegand interface (power, ground, data 0, data 1, and/or beeper and LED). Alternatively, Belden 83559 equivalent or higher quality, for all reader functions.

Contact your access control system manufacturer for their specific requirements. Per the SIA's Wiegand specification, maximum cable length is 500 feet (152 m).

**NOTE:** Unused conductors should be trimmed, isolated and taped back to prevent unintended current flows. Apply positive voltage only to the Red DC Conductor.

### 5.0 Output Formats

Wiegand (industry standard 26 bit Wiegand and custom Weigand formats):

NBT125-W, BT125-W, BT135-W

### 6.0 Grounding

Shield (drain) continuity must run from the reader to the access panel. Shield (drain) and reader ground must be tied together at the access panel and connect to an earth ground at one point.

### 7.0 Power

Reader may be powered by the access panel. A Linear power supply is recommended for best operation.

### 8.0 Voltage

**NBT125:** 8 to 14 VDC, 80mA

**BT125:** 8 to 14 VDC, 60mA Typical, 120mA peak

**BT135:** 8 to 14 VDC, 60mA Typical, 250mA peak

# Access Control Readers

## BLE Mobile / 125 kHz / 13.56 MHz

# LINEAR

## HAF Reader Quick Start Guide

### 9.0 Connection

Connection must be done in accordance with NFPA 70. Do not connect to a receptacle controlled by a switch. Connect to a power limited DC voltage source.

### 10.0 Troubleshooting

1. When the reader is first powered on it will beep 4-times, and the LED will shine red or blue.
2. Presenting a supported access credential will result in the reader beeping and the LED flashing once.

**NOTE: The access panel controls LED functionality, such as switching the LED to green.**

If the reader does not recognize the card or tag (no beep, no LED flash) or exhibits short read range, please see the table below for possible causes and solutions.

Possible Cause	Corrective Action
Incorrect cabling	Verify gauge, connections and cabling length
Not enough power	12 VDC recommended
Incorrect card used	Verify if card technology is supported
Reader/access panel not properly grounded	Earth ground needed - verify shield and reader ground are tied at access panel and connect to ground at one point
Supply generating interference	Linear power supply recommended, verify switching power supply before use

Should any of the corrective actions mentioned above not improve performance, disconnect the reader from the access panel and power it with a separate power supply or 9 VDC battery, and re-test card functionality. By powering the readers separately, most variables that may lead to reduced performance can be eliminated. Should the problem persist, please contact Linear directly.

FCC compliance Statement: This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

Product can be used without license conditions or restrictions in all European Union countries, including Austria, Belgium, Bulgaria, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Poland, Portugal, Romania, Slovakia, Spain, Sweden, United Kingdom, as well as other non-EU countries, including Iceland, Norway, and Switzerland.

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) This device may not cause interference. (2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/recepteur exempt de licence contenu dans le present appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes: (1) L'appareil ne doit pas produire de brouillage; (2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

**Note:** This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Linear reserves the right to change specifications without notice.

Equivalent Models: P-3500, CSB-3500, PB-3500

Many Linear Data Readers carry the following certifications:



### Access Performance Levels

Destructive Level	Line Security	Endurance	Standby Power
Level I	Level I	Level IV	Level I
<b>Operating Temperature:</b> -31°F to +150°F (-35°C to +66°C)			
<b>Operating Humidity:</b> 0% to 90% Relative Humidity			
<b>IP Rating:</b> IP67			

# LINEAR

USA & Canada Toll Free (800) 421-1587  
or dial (760) 438-7000  
www.linear-solutions.com